



Audi A6 (4B) ***All models with parking aid***

Warning buzzer does not work.

If there are complaints with these vehicles that the warning buzzer for the parking aid does not work, one possible cause is a faulty control unit. The entry "Warning buzzer – short-circuit to plus" is stored in the fault memory. In this case, the transistor in the control unit, responsible for triggering the warning buzzer, has failed. To eliminate the fault, the parking-aid control unit must be replaced. The warning buzzer does not need to be replaced.

Note:

Modified transistors have been used in the parking-aid control unit of vehicles from vehicle identification number: 4B1N120000 onwards. In such cases, there may be another reason for the problem.